

54x3w RGB LED Par Light

一: LED display operation center

after power on,press MENU to view Main menu,press UP/DOWN to choose sub-menu,then press ENTER to save.



MENU UP DOWN ENTER

d001	⇒	d512	⇒	3CH mode
A001	⇒	A512	⇒	8CH mode
FF01	⇒	FF99	⇒	RGB color gradual change
CC01	⇒	CC99	⇒	RGB color jump
r001	⇒	r255	⇒	Red manual dimmer
		G255	⇒	Green manual dimmer
		b255	⇒	Blue manual dimmer
		w255	⇒	White manual dimmer
dEoo	⇒	dEoo	⇒	Demo
SoUd	⇒	SoUd	⇒	Sound control
SLAv	⇒	SLAv	⇒	Slave mode

二: DMX channels

3CH mode		
Channel	Value	Function
CH1	0	Red off
	1-255	0-100% dimmer
CH2	0	Green off
	1-255	0-100% dimmer
CH3	0	Blue off
	1-255	0-100% dimmer
8CH mode		
Channel	Value	Function
CH1	0-255	General dimmer
CH2	0	Red off
	1-255	0-100% dimmer
CH3	0	Green off
	1-255	0-100% dimmer
CH4	0	Blue off
	1-255	0-100% dimmer
CH5	0	
	0	
CH6	0-255	Strobe slow to fast
CH7	0-255	Speed slow to fast
CH8	0-50	Open CH1-CH6
	51-100	Programme colors
	101-150	Color gradual change
	151-200	Color fade
	201-250	Color jump
	251-255	Open Sound mode

三: Set Master-Slave

2 lights or more connected with DMX cable,one light set as Demo or color auto change,the others all set as Slave mode.

四: Specifications

Power input : 100-240v , 50/60 HZ

LED : 54x3w RGB 3 in 1

Work Mode : DMX,Auto,Master-slave,Sound

DMX Mode : 3CH and 8CH mode

Beam angle : 25 degrees

Power consumption : 120w