

vintage lights

1. Working voltage: AC220V/50Hz
2. Product power: 250W three 60W golden light 36 pieces 3535 three-in-one lamp beads (3W one)
One 40W four-in-one lamp bead
4. mode: international DMX512, 15 channels,
5. Working mode: DMX512, master/slave, self-propelled, voice control
6. Dimming mode: 0~100% ultra-smooth dimming
7. Strobe: 25 times/second

15 channels	function	DMX value	description
1	X-axis	0-255	0~360 degrees
2	X Wuji	0-49	0-360 degree rotation (speed from fast to slow) X-axis speed enables 360 degree rotation
		50-152	Clockless rotation (fast to slow)
		153-255	Indefinitely reverse clock (slow to fast)
3	Golden light total dimming	0-255	Linear dimming from dark to light
4	Strobe	0	Not functional
		1-255	Synchronous strobe speed from slow to fast (1HZ~25HZ)
5	Golden light	0-4	Extinguish the light
		5-41	Golden light 1
		42-76	Golden light 2
		77-112	Golden Light 3
		113-148	Golden light 1 + golden light 2
		149-184	Golden Light 2 + Golden Light 3
		185-220	Golden Light 1 + Golden Light 3

		221-255	Golden light 1 + golden light 2 + golden light 3
6	Staining total dimming		Linear dimming from dark to light
7	Strobe	0	
		1-255	Synchronous strobe speed from slow to fast (1HZ~25HZ)
8	Dye 1 (dyeing effect running color)	0-4	Extinguish the light
		5-41	red
		42-76	green
		77-112	blue
		113-148	Red + green
		149-184	Red + Blue
		185-220	Green + Blue
		221-255	Red + Green + Blue
9	Staining 2 (dyeing effect base moving color)	0-4	Extinguish the light
		5-41	red
		42-76	green
		77-112	blue
		113-148	Red + green
		149-184	Red + Blue
		185-220	Green + Blue
		221-255	Red + Green + Blue
10	Staining 3	0-4	Extinguish the light
		5-41	red
		42-76	green
		77-112	blue
		113-148	Red + green
		149-184	Red + Blue
		185-220	Green + Blue
		221-255	Red + Green + Blue
11	beam	0-4	Extinguish the light
		5-36	red
		37-48	green
		48-79	blue
		80-111	white
		112-144	Red + green

		145-176	Red + Blue
		177-208	Green + Blue
		209-240	Red++ Green + Blue
		241-255	Red++ Green + Blue + White
12	(Golden Light) macro function	0-4	No effect
		5-85	Built-in effect 1 (slow to fast)
		86-170	Built-in effect 2 (slow to fast)
		171-255	Built-in effect 3 (slow to fast)
13	(Stained light) macro function	0-4	No effect
		4-45	Built-in effect 1 (slow to fast)
		46-87	Built-in effect 2 (slow to fast)
		88-129	Built-in effect 3 (slow to fast)
		130-171	Built-in effect 4 (slow to fast)
		172-213	Built-in effects5 (slow to fast)
		213-255	Built-in effects6 (slow to fast)
14	(beam) macro function	0-4	No effect
		5-85	Built-in effect 1 (slow to fast)
		86-170	Built-in effect 2 (slow to fast)
		171-255	Built-in effect 3 (slow to fast)
15	reposition	0-199	No effect
		200-255	reposition

20 channels	function	DMX value	description
1	X-axis	0-255	0~360 degrees
2	X Wuji	0-49	0-360 degree rotation (speed from fast to slow) X-axis speed enables 360 degree rotation
		50-152	Clockless rotation (fast to slow)
		153-255	Indefinitely reverse clock (slow to fast)
3	Golden light total dimming	0-255	Linear dimming from dark to light

4	Strobe	0	Not functional
		1-255	Synchronous strobe speed from slow to fast (1HZ~25HZ)
5	Golden light 1	0-255	Linear dimming from dark to light
6	Golden light 2	0-255	Linear dimming from dark to light
7	Golden Light 3	0-255	Linear dimming from dark to light
8	Staining total dimming	0-255	Linear dimming from dark to light
9	Staining strobe	0	Not functional
		1-255	Synchronous strobe speed from slow to fast (1HZ~25HZ)
10	Dye red light (dyeing effect running color)	0-255	Linear dimming from dark to light
11	Dye green light (dyeing effect base color)	0-255	Linear dimming from dark to light
12	Stain blue light	0-255	Linear dimming from dark to light
13	Beam red	0-255	Linear dimming from dark to light
14	Beam green	0-255	Linear dimming from dark to light
15	Beam green	0-255	Linear dimming from dark to light
16	Beam white light	0-255	Linear dimming from dark to light
17	(Golden Light) macro function	0-4	No effect
		5-85	Built-in effect 1 (slow to fast)
		86-170	Built-in effect 2 (slow to fast)
		171-255	Built-in effect 3 (slow to fast)
18	(Stained light) macro function	0-4	No effect
		4-45	Built-in effect 1 (slow to fast)
		46-87	Built-in effect 2 (slow to fast)
		88-129	Built-in effect 3(slow to fast))
		130-171	Built-in effect 4(slow to fast)
		172-213	Built-in effect 5 (slow to fast)
		213-255	Built-in effect 6(slow to fast)
19	(beam) macro function	0-4	无作用
		5-85	Built-in effect 1 (slow to fast)
		86-170	Built-in effect 2 (slow to fast)
		171-255	Built-in effect 3 (slow to fast)
20	reposition	0-199	No effect
		200-255	reposition

26 channels	function	DMX value	description
1	X-axis	0-255	0~360 degrees
2	X Wuji	0-49	0-360 degree rotation (speed from fast to slow) X-axis speed enables 360 degree rotation
		50-152	Clockless rotation (fast to slow)
		153-255	Indefinitely reverse clock (slow to fast)
3	Golden light total dimming	0-255	Linear dimming from dark to light
4	Strobe	0	Not functional
		1-255	Synchronous strobe speed from slow to fast (1HZ~25HZ)
5	Golden light 1	0-255	Linear dimming from dark to light
6	Golden light 2	0-255	Linear dimming from dark to light
7	Golden Light 3	0-255	Linear dimming from dark to light
8	Staining total dimming	0-255	Linear dimming from dark to light
9	Staining strobe	0	Not functional
		1-255	Synchronous strobe speed from slow to fast (1HZ~25HZ)
10	Dye red light 1 (dyeing effect running color)	0-255	Linear dimming from dark to light
11	Dye green light 1 (dyeing effect base color)	0-255	Linear dimming from dark to light
12	Stain blue light 1	0-255	Linear dimming from dark to light
13	Staining red light 2	0-255	Linear dimming from dark to light
14	Stained green light 2	0-255	Linear dimming from dark to light
15	Staining blue light 2	0-255	Linear dimming from dark to light
16	Staining red light 3	0-255	Linear dimming from dark to light
17	Staining green light 3	0-255	Linear dimming from dark to light
18	Stain blue light 3	0-255	Linear dimming from dark to light
19	Beam red	0-255	Linear dimming from dark to light
20	Beam green	0-255	Linear dimming from dark to light
21	Beam blue light	0-255	Linear dimming from dark to light
22	Beam white light	0-255	Linear dimming from dark to light
		0-4	No effect

23	(Golden Light) macro function	5-85	Built-in effect 1 (slow to fast)
		86-170	Built-in effect 2 (slow to fast)
		171-255	Built-in effect 3 (slow to fast)
24	(Stained light) macro function	0-4	No effect
		4-45	Built-in effect 1 (slow to fast)
		46-87	Built-in effect 2 (slow to fast)
		88-129	Built-in effect 3 (slow to fast)
		130-171	Built-in effect 4 (slow to fast)
		172-213	Built-in effect 5 (slow to fast)
		213-255	Built-in effect 6 (slow to fast))
25	(beam) macro function	0-4	No effect
		5-85	Built-in effect 1 (slow to fast)
		86-170	Built-in effect 2 (slow to fast)
		171-255	Built-in effect 3 (slow to fast)
26	reposition	0-199	No effect
		200-255	reposition